That's two...

   We must be official! This is our second
issue! Since CLOAD Magazine (for the Models I
and III) was formed 3 years ago, we have seen
quite a few cassette-based magazines fail to get
out issue #1 (let alone #2!!). So we will break
open the champagne once again as this issue of
Chromasette goes to the P.O. (it makes us feel
better when we have an excuse to party at work).
There has been only one complaint - Tom is dis-
covering that he now has to WORK...

```
*****************************************************************************
*                                                                         *
*     Filename      English Translation            PMODE  PCLEAR  Locations *
*                                                                         *
*     HORNCOV       Horn Cover                        3      4      8 & 137 *
*  ·* DRAWINST      Drawer Instructions              (2)    (4)    25 & 151 *
*     DRAWER        Drawer                           0-4     6     45 & 166 *
*     WORDS         Words                            (2)    (3)    63 & 180 *
*     JERUSADV      Jerusalem Adventure               0      1     83 & 196 *
*     LANDER        Lander                           (2)    (4)   107 & 215 *
*     TWODATES      Two Dates                        (2)    (4)   124 & 229 *
*                                                                    use    *
*     Locations are for the R/S CTR-80.  If the first copy of a program    *
*     won't load, try the second.  If neither copy loads, return the tape  *
*     for disciplining and a prompt replacement.  PMODE and PCLEAR values  *
*     in parentheses are not explicitly set in the programs and may have   *
*     to be entered before loading or running the programs.  Otherwise,    *
*     an OM, FC, or SN error may occur.                                    *
*                                                                         *
*****************************************************************************
```

   Horn Cover (named for the occasional time that the graphic resembles a
horn of plenty) is a demonstration of the DRAW command. All the patterns were
created by just manipulating the Scale, Color, No-update, and Angle options of
the DRAW command, and sticking them inside a few FOR-NEXT loops. However,
there is a little tweeking done on the starting positions of each figure so
that they all share a common center.

   You've been playing with your Color Computer a while, but you still don't
quite understand all of the ins and outs of the graphics. Drawer allows you
to really PLAY with the graphic features. You can draw a picture, paint it,
change the colors, move blocks of the screen around, change the start page,
change the PMODE (this one is FUN), save your drawing to tape, etc.

   First, you should run Drawer Instructions. Run 'em a couple of times
until you have a good idea what the Drawer program allows you to do. Does it
seem that there are a lot of options? You're right! Don't be alarmed,
however. If you are drawing away and you want to do one of the options, but
you don't know which one or how to use it, just type 'H' (for Help). You
will then get a thumbnail sketch of all of the commands and a list of all of
   important variables. Then you return to your drawing, armed with your
next command.

   That variable list can be a real lifesaver. More than a few times it
appeared that the program was acting funny. So I hit 'H' and looked at the
variable list. And usually the 'Last Command' variable was something besides
'H'. That meant that the program was waiting for me to finish a previous

command. So I would finish up that command and go back to drawing. The variables also saved me when I wanted to Wash (PAINT) in a figure. I would it 'W', and then try to remember what the foreground and backround colors were. No problem - I just hit 'H' and looked at what the colors were in the variable list.

Special notes - if you have 32K, you can get more than the 6 graphic pages by changing the PCLEAR6 in line 10 to PCLEAR8, changing the MP=6 to MP=8 in line 12, and (for cosmetics) changing the 'P' and 'R' command references in lines 224 and 226 to go from Pages 1-8. Also, stay away from the red joystick buttons. Pressing one of them can cause you to execute a random command (and you'll have to go into the Help subroutine to see what command you're in) since the right joystick button generates @ABCDEFG and the left one generates HIJKLMNO.

More special notes - In a 16K machine, you only have a couple hundred bytes of free memory left after running Drawer. This is plenty for all of the operations... except for Wash (which uses the Extended BASIC PAINT command). If you Wash an intricate drawing, on occasion you will get an OM (Out of Memory) error. Have you noticed how the computer PAINTs? It starts painting down from the specified point, then goes back to fill in those areas it missed. Well, somehow the computer has to keep track of where it has painted to be able to go back to catch the nooks and crannies. It does this by building a 'stack' of numbers representing the boundries of places it still has to visit. As it fills an area with color, it adds to the stack when it encounters an area to be painted on a future pass and takes a value off the stack when it finishes painting an area. Evidently, the stack is stored in the free memory area, so if it gets too large, you get an OM error. There is way to save your drawing, however -

If you get an error during Wash (or any other error other than a SN error), just type 'SCREEN 1,SC : GOTO 20'<enter> right away and save your drawing to tape (with the 'T' option). It takes up to 7 minutes to save the entire screen. Then RUN Drawer again (RUNning cleans up the stack), and load your drawing back in with the 'T' command. If you accidentally hit <break>, you can get back to where you were by typing 'SCREEN 1,SC : CONT'<enter>.

Ok, Drawer sounds like fun, right? But can it really do anything? Many of you told us that you thought last month's cover program was neat. With Drawer, you can easily change that Chromasette banner to say anything you want to! First, you create your own banner following these rules:

1) Be sure you're in PMODE 3 (use the 'G' command).
2) Draw your banner between 0-255 in the X direction and between 0-41 in the Y direction. It is helpful to draw a boundary line across the screen at Y=42. You can get the cursor's X and Y values from the Help command.
3) Do not have more than 4 pixels in a row of Green or Buff. These colors are represented by binary '00', and 4 of them in a row would make a byte with the value of 0. 0 is a special marker in BASIC programs and would be disastrous if it is packed into a string.

Second, you save the block surrounding your banner to tape with the 'T' command. BE SURE that the block you save goes the full length of the screen goes at least from 0 to 41 in the Y direction (you can save a little more in the Y direction but only the first 42 lines are used by the cover program).

Now, load in last month's First Cover and add the following code:

```
69 GOTO 30000
30000 CLS : INPUT"<ENTER> WHEN CASSETTE READY TO LOAD":0
```

```
30020 VP=0 : AD=0 : I=0 : J=0 : REM DECLARE VARS TO BE USED
30030 INPUT#-1,Q,Q,Q,Q : REM GET RID OF EXTRA VALS USED BY DRAWER
30040 FOR I = 0 TO 6 : REM TO FILL UP 7 STRINGS
30050 VP=VARPTR(LO$(I)) : REM GET STRING DESCRIPTOR
30060 AD=PEEK(VP+3)+PEEK(VP+2)*256 : REM GET STRING LOCATION
30070 FOR J = 0 TO 191 : REM DO ALL BYTES IN STRING
30080 INPUT#-1,Q : REM GET GRAPHIC BYTE
30090 POKE(AD+J),Q : REM PUT GRAPHIC BYTE IN STRING
30100 NEXTJ : NEXTI
30110 CLOSE : DEL 69 : REM STRINGS NOW PACKED - RUN COVER AGAIN
```

Run the modified cover program, load in the data you got from Drawer, then run the cover program again to see your handywork! Thankees - this idea came from the local Radio Shack Computer Center.

Words is the first in a probably long series of unscramble-the-word programs that I will see. And you may even catch more than a couple of them.

Treasures worth their weight in oil! How do you get them? Let's go on a little Jerusalem Adventure. For those of you who are unfamiliar with 'role playing' games (hee, hee, hee), you may have a couple of frustrating hours trying to get off that @#*&%@$ street in Jerusalem. You see, you are an adventurer in this unfamiliar city, and you are trying to find 9 treasures located somewhere around there. By observing your surroundings and giving the appropriate commands, you collect treasures and get hints on how to get around other obstacles in order to find more treasures.

Be forewarned! If you find yourself stuck in Jerusalem Adventure and you ant help, calling here may not be a good idea. I take sadistic pleasure in not giving hints to adventure games! However, I may be a bit nicer since it is quite tricky to get off that street in Jerusalem. Then again, maybe I'll just go for greater personal pleasure...

Lander is the first in a probably long series of land-on-the-planet programs that I will see. And you may even catch more than a couple of them. Haven't you read this before?

Dave-of-a-thousand-days. If it starts August 14, 1981, it ends May 10, 1984. See what useful data you get from Two Dates? You give it the first date, then you give it a date displacement or a new date, and you get the monthly calendars for both dates as well as the number of days between the dates. You can also assign a daily or weekly value to be calculated. This program is only accurate from March 1, 1900 to February 28, 2100, so if you plan to time-travel with it, don't go too far! Or modify the program to NOT give you a leap year in years ending in '00' unless they are divisible by 400. I didn't modify the program because: a) I was lazy or, b) you needed a challenge. I like 'b' better.

Damn the interpreter, full space ahead! - This month's debug it lesson.

You have just typed a 3 line program in your pretty beast, and now it won't run correctly. You do a little detective work, and line 20 seems to be the culprit:

```
10 INPUTA,B
20 IFA>=BTHENPRINTAELSEPRINTB
30 GOTO10
```

According to the manual, it is syntactically correct!!! Now what? Well, retype line 20 and spread it out a bit:

    20 IF A>=BTHENPRINTAELSEPRINTB : REM SPACE AFTER IF

That didn't help, so let's try again -

    20 IFA>=B THENPRINTAELSEPRINTB : REM SPACE BEFORE THEN

    Hey, we don't get a SN error! But the value printed out isn't right
either. Durn it! Ok, time to hit line 20 again:

    20 IFA>=B THEN PRINTAELSEPRINTB : REM SPACE BEFORE PRINT

Bugs still. Go for another round -

    20 IFA>=B THENPRINT AELSEPRINTB : REM SPACE AFTER PRINT

Bah, humbug! One more try before trashing this computer:

    20 IFA>=B THENPRINTA ELSEPRINTB : REM SPACE BEFORE ELSE

    Yahoo! Woopie! And it only took 2 hours! Sure is strange... what if we
retype the line as:

    20 IFA>=2THENPRINT1ELSEPRINTB : REM PUT #S BEFORE THEN AND ELSE

    Now the program doesn't do anything worthwhile, but it does work. From
this exercise we can make this hypothesis (can't we?):

    All keywords (those words recognizable by BASIC) must be preceded by:
        1)   a space,
        2)   a number,
        3)   some punctuation, or
        4)   another keyword.
    or you get funny (?) results.

    Movin' up in the world...

    There are a couple of interesting things for the Color Computer coming
from Radio Shack yesterday - that is, they have been announced and are in the
catalog but I haven't seen them yet.

    You can get another 16K for your machine! I understand that the chips
will be piggy-backed somehow (wonder what happened to the ol' heat problem?).

    You can get disks! Your local R/S service center has to go into your baby
and hack a bit (something about adding jumpers and adding RF shielding), but
you get up to 4 disks connected at the cartridge slot. A preliminary list of
the DOS commands showed the Color DOS to be similar to TRSDOS. And the disk
drives themselves are Shugarts with a 35 track format. Ok, where is this
stuff?!!

    Promises, promises....

    As promised last month, on the next page you will find the source listings
of the various machine language routines used in First Cover (and subsequent
covers), Blockade, and Jerusalem Adventure. These routines were used mainly
to assist in moving blocks of data around quickly, so they are rather simple.
Also, they are relocatable (Jerusalem Adventure places data in a fixed
location, however) so the origin of the routines is arbitrary.

                                          Off to the hills,

;This takes data from the strings LO$(0-6) in cover programs
;and puts in the graphic screen memory moving left to right.
;

```
3000    8D B3ED     JSR   B3ED      ;Get addrs of LO$(0) from BASIC
3003    1F 01       TFR   D,X       ;  and put it in X register
3005    108E 05FF   LDY   #35FF     ;Initialize screen column pntr.
3009    86 20       LDA   #20       ;Put 32 column count
300B    34 02       PSHS  A         ;  on stack
300D    A6 A0       LDA   Y+        ;Increment screen column pntr
300F    34 20       PSHS  Y         ;  and put on stack
3011    34 10       PSHS  X         ;Push strings pointer on stack
3013    86 07       LDA   #07       ;Push 7 strings count
3015    34 02       PSHS  A         ;  on stack
3017    C6 06       LDB   #06       ;Init 6 rows per string count
3019    A6 84       LDA   0,X       ;Get byte from string and
301B    A7 A4       STA   0,Y       ;  stick it on the tube
301D    1E 01       EXG   D,X       ;Add 32 (by subtracting -32)
301F    83 FFE0     SUBD  #FFE0     ;  to string and screen pntrs
3022    1E 01       EXG   D,X       ;  to go on to next row
3024    1E 02       EXG   D,Y
3026    83 FFE0     ADDD  #FFE0
3029    1E 02       EXG   D,Y
302B    5A          DECB            ;Dec row per string count and
302C    26 EB       BNE   3019      ;  cont. if more rows in string
302E    1F 10       TFR   X,D       ;Add 14 (subtract -14) to strng
3030    83 FFF2     SUBD  #FFF2     ;  pntr to point to next string
3033    1F 01       TFR   D,X
3035    35 02       PULS  A         ;Get string count from stack
3037    4A          DECA            ;Dec and do another string if
3038    26 DB       BNE   3015      ;  more strings to do
303A    35 10       PULS  X         ;Get initial string column pntr
303C    A6 80       LDA   X+        ;  and inc to next column
303E    35 20       PULS  Y         ;Get initial screen column pntr
3040    35 02       PULS  A         ;Get column count and
3042    4A          DECA            ;  dec - if columns not done
3043    26 C6       BNE   300B      ;  go do next column
3045    39          RTS             ;Home, James - back to BASIC
```

;This routine takes the banner at the top of cover and copies
;it to another location on the screen. The inst. at 3014 is a
;NOP if the copied banner is to have the same colors as orig.
;This walks through and copies the banner backwards.
;

```
3000    8D B3ED     JSR   B3ED      ;Get displacement from BASIC
3003    C3 10C0     ADDD  #10C0     ;  and add base (save top logo)
3006    1F 01       TFR   D,X       ;Put new address in X
3008    108E 0860   LDY   #0860     ;Put last logo location in Y
300C    86 2B       LDA   #2B       ;Get lines count
300E    34 02       PSHS  A         ;Put lines count on stack
3010    C6 20       LDB   #20       ;Init bytes per line to 32
3012    A6 A2       LDA   -Y        ;Get logo byte and dec logo loc
3014    43          COMA            ;Flop color (or NOP if no flop)
3015    A7 82       STA   -X        ;Put at new logo (dec new loc)
3017    5A          DECB            ;Dec bytes per line and
3018    26 F8       BNE   3012      ;  do more if more left
301A    35 02       PULS  A         ;Get lines count and
301C    4A          DECA            ;  dec - do another line if
301D    26 EF       BNE   300E      ;  more left
301F    39          RTS             ;Go home to BASIC
```

This routine takes the block location passed from Block code and
;returns the X, Y, X+7, Y+7 values needed by the BASIC JL
;command. It is actually 4 similar routines so just the source
;for the X and Y routines will be given here.
;
;** Y value **

```
3000    8D B3ED     JSR   B3ED      ;Get block location
3003    1F 01       TFR   D,X       ;  and put it away
3005    4F          CLRA            ;Zero Y count
3006    5F          CLRB
3007    5C          INCB            ;Inc Y count
3008    1E 01       EXG   D,X       ;Get block location and
300A    C3 FFE0     ADDD  #FFE0     ;  subtract 32 (add -32)
300D    1E 01       EXG   D,X       ;Get Y count
300F    2C F6       BGE   3007      ;Do another if block loc >=0
3011    5A          DECB            ;Get rid of extra Y count
3012    7E B4F4     JMP   B4F4      ;Send Y to BASIC
```

;** X value **

```
3015    8D B3ED     JSR   B3ED      ;Get block location
3018    C3 FFE0     ADDD  #FFE0     ;Subtract 32 (add -32) until
301B    2C FB       BGE   3018      ;  block loc <0
301D    83 FFE0     SUBD  #FFE0     ;Add 32 (subtract -32)
3020    86 08       LDA   #08       ;Multiply by 8 for 8 X counts
3022    3D          MUL             ;  per byte
3023    7E B4F4     JMP   B4F4      ;Send X to BASIC
```

;The following routines were used to achieve the split screen
;effect used in Jerusalem Adventure. The second routine stores
;every byte of the screen into the graphics screen area until
;it hits an '='. The first routine takes the stored stuff and
;puts it back on the screen.
;

;** Storage to Screen **

```
2800    8D B3ED     JSR   B3ED      ;Get PRINT @ loc. from program
2803    8E 0600     LDX   #0600     ;Start of storage (source)
2806    108E 0400   LDY   #0400     ;Start of screen mem (dest.)
280A    FD 0800     STD   0800      ;Save PRINT @ from harm
280D    A6 80       LDA   X+        ;Get source byte and
280F    A7 A0       STA   Y+        ;  stick it on the screen
2811    FC 0800     LDD   0800      ;Get PRINT @ and
2814    83 0001     SUBD  #0001     ;  decrement and
2817    26 F1       BNE   280A      ;  do it again until done
2819    39          RTS             ;Go home
```

;** Screen to Storage **

```
281A    8E 0400     LDX   #0400     ;Start of screen (source)
281D    108E 0600   LDY   #0600     ;Start of storage area (dest.)
2821    A6 84       LDA   0,X       ;Get byte to stuff from screen
2823    E6 80       LDB   X+        ;Get screen byte to test
2825    C0 7D       SUBB  #7D       ;  and if byte is '='
2827    27 04       BEQ   282D      ;  stop stuffing
2829    A7 A0       STA   Y+        ;Stuff byte in storage area
282B    20 F4       BRA   2819      ;Go get another byte
282D    1E 01       EXG   D,X       ;Get last screen mem loc used
282F    83 0401     SUBD  #0401     ;  and make it into a PRINT @
2832    7E B4F4     JMP   B4F4      ;  location - send it to BASIC
```